

ボルトスライダ仕様書		仕様書番号	1 - 9 1 1	製 作 者	井上 '08.02.04
		関連図面	S - 1 4 0 0 4 - (1)		
型 式 S - 1 3 0 - 3 0					
方 式	1 . 操作 (・ 手動) ・ 電動 ・ 手動 / 電動		4 . 巻線 (・ 単巻) ・ 複巻		
	2 . 冷却 (・ 乾式)				
	3 . 設備 (・ 据置) ・ 取付 ・ 移動		5 . その他		
入 力	6 . 相数 (・ 単相) ・ 3 相 3 線 ・ 単相 3 線		9 . 定格電圧 <u>1 0 0</u> V		
	7 . 周波数 (・ 50Hz) (・ 60Hz) ・ _____ Hz		10 . 電圧変動率 _____ %		
	8 . 3 相結線 Y , V , - , Y - , - Y		11 . 定格時間 ・ 連続 (・ 最大) <u>4</u> H		
出 力	12 . 相数 (・ 単相) ・ 3 相 3 線 ・ 単相 3 線		16 . 定格電流 <u>3 0</u> A		
	13 . 最大電圧 <u>1 3 0</u> V		17 . 容量 <u>3</u> kVA <u>1 0 0</u> V時		
	14 . 電圧調整範囲 <u>0</u> ~ <u>1 3 0</u> V		18 . 電圧変動率 <u>5</u> % <u>1 3 0</u> V時		
	15 . 電圧調整段階電圧 (・ 連続) ・ _____ V 毎		19 .		
温 度 上 昇	20 . コイル <u>9 0</u> 以下 但し、ブラシ直下 1 / 2 タ - ンの位置				
	21 . 鉄芯 <u>8 5</u> 以下				
	22 . トランス _____ 以下				
そ の 他	23 . 絶縁抵抗 <u>1 0</u> M <u>5 0 0</u> Vメガ		26 . 塗装色 ・ <u>マンセル 5 Y 7 / 1</u>		
	24 . 絶縁耐力 <u>1 5 0 0</u> V 1 分間 商用周波数		27 . 摺動時間 約 _____ 秒		
	25 . 付属品 (・ 無し) ・ あり		28 . モ - タ - 電源電圧 AC . 1 _____ V		
備 考	29 . 概算重量 <u>1 5</u> kg				
結 線 図					
<p>The diagram shows a vertical black bar representing the device. On the left side, there are two input terminals labeled 'U' and 'V', each with a circled cross symbol. On the right side, there are two output terminals: the top one is labeled 'μ' and the bottom one is unlabeled, both with circled cross symbols. Arrows point from the input terminals towards the bar and from the bar towards the output terminals. The word 'INPUT' is centered below the left terminals, and 'OUTPUT' is centered below the right terminals.</p>					